

## Mini Mixer Amplifier 30W/60W/120W/180W SP-MH30, SP-MH60, SP-MH120, SP-MH180

### Feature:

- Mini Mixer Amplifier with multi audio inputs for paging & background music system.
- Elegant appearance and high reliable performance.
- Mini table-top design for commercial audio and industrial public address.
- Integrate pre amplifier and power amplifier.
- Ideal for classroom, retail store, small restaurant, office background music and paging system.
- Rated power 30W/60W/120W/180W.
- 100V/70V and low impedance 4Ω-16Ω speaker outputs for versatile connections.
- Built-in Bluetooth, USB/SD, Mp3 and FM.
- 2 XLR Mic input, 2 Line input by RCA on rear panel.
- One RCA Pre-Out, 2 Antenna on the rear panel
- 6 knobs volume control for Input 1-2, Media, bass, treble and master.
- Support DC 24V, support AC110-120V and AC220-240V switchable.
- With natural cooling fan to control internal temperature.
- Overall protection of short-circuit, overload and high temperature to avoid any damage.



### Specification:

Model	SP-MH30	SP-MH60	SP-MH120	SP-MH180
Description	Mini Mixer Amplifier			
Rated Power	30W	60W	120W	180W
Built-in Sources	Bluetooth, USB/SD, Mp3/FM, 2 Mic, 2 Line in, 1 Pre-Out			
Speaker Output	100V/70V & 4Ω-16Ω			
Frequency Response	100Hz~20KHz			
THD	<0.5% at 1 KHz 100V -3dB			
S/N Ratio	75dB			
Input	MIC: 1mV/600Ω, AUX: 500mV/10KΩ			
Volume Control	Input 1-2, Media, bass, treble and master			
Tone Control	BASS: 100Hz (±10dB), TREBLE: 10kHz (±10dB)			
Cooling Method	Automatic FAN strong air cooling method			
Protection	Overheating, overload, short circuit, alarm protection			
Power Supply	AC 110~120V 50/60Hz T2AH AC 220~240V 50/60Hz T1AH			
Dimension	220*66*200mm(W*H*D)			

### Appearance:

