

SP-PRU100 10 Channel Pre-Amplifier with Bluetooth USB FM Remote



Feature:

- Rack mount 19" 2U 10 channel mixer pre-amplifier with audio source.
- Individual 10 Inputs & 3 Outputs pre-amplifier for Public Address System.
- Connect with power amplifier and audio source player.
- Each channel with independent volume adjustment.
- Support Bluetooth, USB/Mp3 and FM.
- 10 Audio Inputs (5 Microphone, 4 Line/AUX, 1 Emergency).
- 3 Audio Outputs (1 XLR balanced, 2 RCA unbalanced).
- Microphone with Phantom DC48V power supply.
- Microphone input with priority function, volume can adjust.
- EMC as the highest priority function.
- With 5 LED indicator.
- 13 volume knob independent volume control.
- IR remote control.



Specification:

Model	SP-PRU100
Description	10 Channel Pre-Amplifier
Functions	Bluetooth, USB/Mp3 and FM 10 Audio Inputs, 3 Audio Outputs
AUX/MIC	AUX1-2: 500mV/10Kohms (Ω), MIC1-3: 1-6mV/MIC 1 at 48V
Frequency Response	80Hz ~ 20KHz (± 3 dB)
S/N Ratio	75dB
THD	<0.5% at 1KHz 100V -3dB
Tone Control	Bass: 100Hz ± 10 dB, Treble: 10Hz ± 10 dB
Protection	AC FUSE T1AH 250VAC
Power Consumption	10 ~ 15W
Power Supply	AC220V~240V/50~60Hz
Material	High-end metal panel, 2U Case: steel plate, black, elegant appearance
Net Weight/Dimension	5.5 KG / 88 (H) \times 485 (W) \times 340 (D) mm
Gross Weight/Package	6.95 KG / 550*455*183mm, 1pc/ctn

