

8 Zones Digital Timer Mp3 Player with USB/FT & FM Radio SP-8TM



Feature:

- Rack mount 2U Public address system intelligent controller.
- Ideal for school, restaurant, shopping mall, hotel, and intelligent office etc.
- All in one intelligent PA system controller built in weekly timer, 8 zone speaker selector, Mp3 player & FM, fire alarm and voice evacuation system interface, monitor and programmable power sequencer.
- One amplifier or 4 amplifier inputs divided into 8 zones speaker output.
- Built-in 5W Hi-Fi monitor speaker with volume control.
- With one microphone input, one line input, one USB input and one EMC input and two line outputs
- Auto timely broadcast up to 99 program sources.
- Broadcast modes: random, repeat and circle.
- 4 regular programs and 1 spare program for emergency/particular circumstance.
- Functional swift key for internal MP3 player priority manual broadcast.
- Flash memory capacity support 4GB and 8GB.
- Audio source format support Mp3/MAV and WMA
- The system communication distance up to 1kms
- Memory function even in case of power off.
- Optional: support remote control to play music

Specification:

Model	SP-8TM
Description	PA System 8 Zones Digital Timer Mp3 Player with USB/FT & FM
Timer Function	regularly play music by TF card or USB
Amplifier Input	1 or 4 Amplifier inputs
Zone Output	8 zone speaker outputs, 100V or 70V
Mic Input	5~8mV, 600ohms(Ω), unbalanced
Line Input	300mV , 10k ohms(Ω), unbalanced
Line1-2 Output	10k ohms(Ω) 500mV (0 dB), unbalanced
Memory Capacity	4GB
Program AC Power Outputs	4 outputs
Monitor Speaker	Hi-Fi Full range speaker 5W, 8ohms(Ω)
S/N Ratio	>90dB
Frequency Response	20 Hz ~ 18k Hz
Power Cord	(3 x 0.5mm ²) x 1.5M (standard)
Power Supply	AC 220V \pm 10%, 50-60Hz
Power Consumption	15W ~ 20W
Material	High-end aluminum panel, 2U, brushed black Case: steel plate, black, elegant appearance
Net Weight/Dimension	6.42KG / 89(H) \times 483(W) \times 350(D)mm
Gross Weight/Package	8.22KG / 185 \times 520 \times 435mm, 1pcs/ctn

