

SP-ME60S Mixer Amplifier



Features:

- Tabletop Mini size compact Blue-tooth Mixer amplifier for paging and background music system.
- Ideal for small to medium PA installations such as school coffee shops, classrooms, retail store, restaurants.
- Rate power output at 60W
- Built-in Blue-tooth receiver and USB player.
- Speaker output of 100V & 70V & 4-16 Ohms.
- Two RCA input for AUX.
- Two 6.35mm jack Mic input.
- One RCA output for REC.
- IR Infra-red remote control.
- Individual volume controller for Mic 1, Mic 2, master, bass and treble tone controllers.
- SMT circuit boards with highly stable performance
- High-definition display for the working status of playing programme.
- Complete protection is provided for output short circuit, overload, high temperature, peak current limiters.

Specifications:

Model Number	ME60S
Output Power	60W
Speaker Output	100V & 70V & 4-16 Ohms
Audio Output	RCA Line out for REC
AC Power Supply	AC 100~240V/50-60Hz
Power Consumption	80W
Dimension	213x253x73mm